

If the pattern has a double line around it, the seam allowances are included.

Note: By default, seam allowances are NOT included (single line) and will need to be added when laying out and cutting details.

Seam Allowance: 1 cm on all seams; hem guidelines are printed on pattern.

Important! Please print all the paper patterns and lay them out at the width of fabric you plan to use (usually from 90 to 150 cm) to see how much fabric you will need.

Don't forget to take into account pieces to be duplicated or cut on a fold. When sewing the garment, pay attention to notches. They must match up with corresponding pieces.

2200 Blouse with Gathers and Long Raglan Sleeves

Recommendations on fabric: thin natural/mixed fabrics suitable for blouses. For example, chiffon.

You will also need: fusible interfacing; elastic tape, its width should equal 1 cm; 3 buttons.

CUTTING:

The word, “beam” used on some patterns means “straight of grain”. Some pieces will be cut on the fold, this is noted on the pattern piece. Mark all notches and other design features such as darts, pleats etc. from the pattern onto your fabric.



Seam allowances: all seams 1 cm. Seam allowance along the lower edge of the garment – 1.5 cm. Seam allowance along the upper and middle edge of the stand collar – 0 cm.

Main fabric:

1. Back – cut 1 on fold
2. Front – cut 2 on fold
3. Sleeve – cut 2
4. Cuff – cut 2
5. Stand collar – cut 1 on fold

6. Neckline trimming – cut 1

Fusible interfacing:

1. Cuff – cut 2

INSTRUCTIONS:

1. Apply fusible interfacing.
2. Pin fronts right sides together. Mark the slit line. Stitch 1 mm on each side of the slit (towards the armhole) on both sides. Cut between the stitches, turn pieces right side out, straighten the slit, and press. Treat the fronts as one piece from this point.
3. Sew a gathering stitch along the upper edge of the front and gather fullness.
4. Cut a slit on the sleeve along the marked line. Cut bias tape from the main fabric (or use ready-made), 4 cm wide and as long as twice the slit length plus 4 cm. Fold the bias tape in half lengthwise and press. Press outer seam allowances towards the center. Sew the bias tape to the sleeve slit (pin bias tape to slit edge from the right side and stitch, fold bias tape to the wrong side, and topstitch along the fold line).
5. Sew sleeves to the back, press seams towards the back, and serge. Sew sleeves to the front, press seams towards the front, and serge.
6. Sew side seams, continuing through the sleeve seams. Serge and press.
7. Finish the upper and center edges of the stand collar with a narrow rolled hem. Sew a gathering stitch along the lower edge of the stand collar and gather fullness.
8. Fold the neckline trim in half lengthwise, right sides together, and sew the short edges. Turn the piece right side out and press. Place the stand collar on the garment, right sides together, insert the neckline trim between them, and stitch. Press towards the stand collar and serge. Topstitch the fold of the trim onto the stand collar from the right side, securing the seam allowances.
9. Cut (or prepare) bias tape 2.5 cm wide and 5 cm long for the loop buttonhole. Fold the tape in half lengthwise, right sides together, and stitch 0.3 cm from the fold. Trim seam allowances close to the seam, turn right side out, and straighten into a rolled hem. Adjust the loop length. Sew the button loop to the right side of the stand collar from the wrong side.

10. Pin cuffs right sides together and sew side and lower edges, starting and stopping exactly at the marked seam line. Turn the piece right side out and press. Sew a gathering stitch along the lower edge of the sleeve and gather fullness. Sew the outer cuff to the sleeve, fold in the seam allowance of the inner cuff, and stitch in the ditch along the outer cuff seam.
11. Serge the lower edge of the garment. Press to the wrong side and topstitch to form a casing. Insert elastic tape into the casing and sew the ends together.
12. Make buttonholes on the cuffs, sew on buttons, and sew a button to the left side of the stand collar.

Congratulations – your blouse are finished! :)